

PLENA all-in-one 90W mixer amplifier

www.boschsecurity.com



BOSCH
Invented for life



- ▶ 4 microphone inputs with independent level control
- ▶ USB drive and SD card for MP3 playback
- ▶ Built-in FM tuner with preset memories
- ▶ 100V/Telephone input with priority and VOX
- ▶ 24 VDC backup power supply input

The PLENA all-in-one mixer amplifier is a versatile solution for public address, emergency announcements and back-ground-music (BGM) requirements. This high-performance device is easy to install and operate.

Typical applications of PLENA all-in-one 90W mixer amplifier include use in supermarkets, restaurants, schools, retail chains, canteens, places of worship, gymnasiums etc where BGM provides the right atmosphere, at the same time announcements can be made clearly and with ease.

System overview

The All-in-one unit can provide hours of uninterrupted music from USB or SD flash memory. The unit also has a built in FM tuner with presets. To ensure for optimum performance, the All-in-one unit has no moving parts, such as hard drives that can fail or wear out. The unit is supplied with an IR remote control for controlling the music source. The unit can be rack mounted by using the brackets that can be procured separately.

Functions

Microphone and line inputs

The mixer amplifier has four microphone inputs. Separate level controls are available for all the inputs. For all the inputs (except Aux input), phantom power can be switched on to provide power to condenser microphones. Inputs 1 and 2 can be configured between line and mic level sensitivity. Input channel 1 can take priority over all other microphone and music inputs. Input 1 can be activated by contact closure on the PTT (push to talk). For input 1, a 2-tone chime can be configured to precede an announcement.

Music source and music input

The unit has one music input and an internal music source. There is a source select button on the front panel to select between auxiliary input and internal music source. The internal music source plays MP3 files from an SD/MMC card or USB device with a capacity of up to 32 GB. The player will automatically search and play all playable MP3, WMA files and has repeat and random play modes. The following formats are supported: MP3, WMA files with bit-rates from 32 kbit/s.

FM Tuner

The digitally controlled FM tuner uses a frequency synthesizer for accurate capture of radio stations and has five presets to store favorite radio stations.

Integration

A 100V emergency/telephone input with VOX activation is provided for easy integration with another PA system or a telephone paging system. It has its own preset volume control and overrides all other inputs, including music input and mic/line inputs. The unit also has a line output to add booster amplifiers for larger systems with more output power. The unit has a 24 VDC input for backup power supply.

Outputs

An LED VU meter monitors the master output. A headphone socket, below the VU meter, provides the mixer output. The power is directly available on 100 V or 70V constant voltage connections and on a low impedance connection for a 4 ohm load.

Controls and indicators**Front Panel**

- Power on switch and LED
- LED VU meter for master output
- Master volume control
- Four volume control knobs for microphone inputs
- Volume knob for background music
- Source select button for music source
- Knob for treble level
- Knob for bass level
- Headphone socket

Rear Panel

- Four Inputs and one Aux input
- Dip switches
- Master output
- Telephone/Emergency input with volume control
- 100V,70V and 4 Ohm loudspeaker outputs
- 24 VDC Backup input

Certifications and approvals

Safety	acc. to EN 60065
EMC emission	acc. to EN 55103-1
EMC immunity	acc. to EN 55103-2

Parts included

Quantity	Components
1	All-in-one mixer amplifier
1	Power cord
1	Remote control for Music source
1	FM Antenna with connector
1	Installation and Operating Manual

Technical specifications**Electrical**

Mains Power Supply	
Voltage	230 VAC, $\pm 15\%$, 50Hz
Inrush Current PLN-1AIO090-IN	9A
Battery power supply	
Voltage	24 VDC, $\pm 15\%$, with reverse protection
Current	6.8 A
Performance	
Frequency response	50Hz to 20kHz (+1/-3dB@ -10 dB ref. rated output)
Distortion	< 1% @ rated output power, 1 kHz
Low Control	Max -8/+8 dB
Hi Control	Max -8/+8 dB
Inputs	
Input 1 (push-to-talk contact with priority)	5-pin Euro style, balanced, phantom
Input 2	3-pin XLR, balanced, phantom
Input 3 and 4	TRS Jack (1/4, 6.3 mm), balanced, phantom
Sensitivity	1 mV (mic); 200 mV (line)
Impedance	≥ 1 kohm (mic.); >5 kohm (line)
S/N at rated power	≥ 60 dB (mic); >65 dB (line)
CMRR (mic.)	>40 dB
Phantom power supply	9V via 1.2 kohm (mic)
Speech filter	-3 dB @ 315 Hz, high-pass, 6 dB/oct
Music Input	
Connector	Cinch, stereo converted to mono
Sensitivity	200 mV
Impedance	22 kohm
S/N at rated power	≥ 70 dB
Master Output	
Connector	3-Pin XLR, balanced
Nominal level	1 V
Input Impedance	<100 Ohm
Emergency/Telephone Input	
Connector	5-pin, Euro style pluggable screw terminal

Sensitivity (telephone)	100 mV – 1 V adjustable
Sensitivity (100 V)	10 V - 100 V adjustable
Impedance	>10 kohm
S/N at rated power	>65 dB
VOX	Threshold 50 mV; attack time 150 ms; release time 2 s
Loudspeaker Output	100V, 70V and 4 Ohm
Connector	Euro style pluggable screw terminal, Floating
Max./Rated Power	120W/90W
Loudspeaker Output from 4 Ohm	19.0V from 4 Ohm output

Mechanical

Dimensions (H x W x D)	100 x 430 x 270 mm
Mounting	Stand-alone, 19" rack
Color	Charcoal
Weight	Approx. 6.5 kg

Environmental

Operating temperature	-10 °C to +55 °C
Storage temperature	-40 °C to +70 °C
Relative humidity	<95%

Ordering information

PLENA all-in-one 90W mixer amplifier
 Order number **PLN-1AIO090-IN**

Represented by:

Americas:
 Bosch Security Systems, Inc.
 130 Perinton Parkway
 Fairport, New York, 14450, USA
 Phone: +1 800 289 0096
 Fax: +1 585 223 9180
 security.sales@us.bosch.com
 www.boschsecurity.us

Europe, Middle East, Africa:
 Bosch Security Systems B.V.
 P.O. Box 80002
 5617 BA Eindhoven, The Netherlands
 Phone: + 31 40 2577 284
 Fax: +31 40 2577 330
 emea.securitysystems@bosch.com
 www.boschsecurity.com

Asia-Pacific:
 Robert Bosch (SEA) Pte Ltd, Security Systems
 11 Bishan Street 21
 Singapore 573943
 Phone: +65 6571 2808
 Fax: +65 6571 2699
 apr.securitysystems@bosch.com
 www.boschsecurity.asia

China:
 Bosch (Shanghai) Security Systems Ltd.
 201 Building, No. 333 Fuquan Road
 North IBP
 Changning District, Shanghai
 200335 China
 Phone +86 21 22181111
 Fax: +86 21 22182398
 www.boschsecurity.com.cn

America Latina:
 Robert Bosch Ltda Security Systems Division
 Via Anhanguera, Km 98
 CEP 13065-900
 Campinas, Sao Paulo, Brazil
 Phone: +55 19 2103 2860
 Fax: +55 19 2103 2862
 latam.boschsecurity@bosch.com
 www.boschsecurity.com